

## PHASE SEQUENCE INDICATOR SQ 0201 AND TEMPERATURE METERS



SQ 0201



KQ 0x07

A phase sequence indicator is intended for determining phase sequences in a three-phase network, from 200 V to 500 V and from 50 Hz to 60 Hz. The indicator is provided with two built-in glow lamps indicating L1, L2, L3 phase sequence.

Temperature meters are intended for connection to various thermocouples or temperature dependant resistors with the possibility of analogue output. The accuracy class is 1.5.

TYPE		KQ 0307	KQ 0307	KQ 0207	KQ 0207
Front frame (mm)		72 x 72	72 x 72	96 x 96	96 x 96
Cutting for mounting (mm)		68 x 68	68 x 68	92 x 92	92 x 92
Scale length (mm)		65	65	95	95
ANALOGUE OUTPUT		-	0...10 mA Rmax. = 200 Ω	-	0...10 mA Rmax. = 200 Ω
MEASURING RANGE					
Resistor probe Pt 100	+/-50° C	•	•	•	•
	0...100° C	•	•	•	•
	0...200° C	•	•	•	•
	0...300° C	•	•	•	•
	0...400° C	•	•	•	•
Thermocouple J Fe-CuNi	0...200° C	•	•	•	•
	0...400° C	•	•	•	•
	0...600° C	•	•	•	•
Thermocouple K NiCr-Ni	0...600° C	•	•	•	•
	0...800° C	•	•	•	•
	0...1200° C	•	•	•	•
Thermocouple S PtRh-Pt	0...1400° C	•	•	•	•
	0...1600° C	•	•	•	•

Supply: 230 V ∞ +/-10% (50...60 Hz)

Other thermocouples on request.

On request: KQ 0207, KQ 0307

110 V +/-10% (50...60 Hz)