

WQ 0217, WQ 1217, WQ 0207, WQ 2207, WQ 1247

Energy meters display instantaneous power in single and three-phase systems with balanced or unbalanced load. Accuracy classes are 1 for energy measurement (EN 61036), 1.5 for power measurement and 2.5 power factor measurement.



WQ 1217



WQ 2207

| TYPE | WQ 0217 | WQ 1217 | WQ 0207 | WQ 2207 | WQ 1247 |
|--|---------|---------|---------|---------|-----------|
| Front frame (mm) | 96 x 96 | 96 x 96 | 96 x 96 | 96 x 96 | 96 x 96 |
| Cutting for mounting (mm) | 92 x 92 | 92 x 92 | 92 x 92 | 92 x 92 | 92 x 92 |
| Scale length (mm) / Number of counters | - / 1 | - / 2 | 95 / 1 | 125 / 1 | - / 2 LCD |
| Voltage input 100 V, 110 V, 230 V, 400 V, 500 V | | | | | |
| Current input 1 A, 5 A | | | | | |
| 1b, 1br Single phase system | • | • | • | • | • |
| 3b, 3br Three-phase three-wire balanced load system | • | • | • | • | • |
| 3u, 3ur Three-phase three-wire balanced load system | • | • | • | • | • |
| 4b, 4br Three-phase four-wire balanced load system | • | • | • | • | • |
| 4u, 4ur Three-phase four-wire unbalanced load system | • | • | • | • | • |
| Option | | | | | |
| One impulse output | • | • | • | • | • |
| Two impulse outputs | • | • | • | • | • |
| 57 V, 110 V, 230 V, 400 VAC Auxiliary supply | • | • | • | • | • |